

PS04

Linear power supply



Overview

Access control, electric lock special linear power controller (3A), using original high-quality imported components, safe, reliable, durable. It is specially designed for various access control systems and building intercom systems.

Product Model

Model	Description
PS04	Iron surface/size: 182*79*62mm/gray

Features

- 1、 Professional design, especially suitable for security projects such as access control;
- 2、 Intelligent design, more effective protection of equipment and supporting products;
- 3、 Produced with high-quality components, safer and more stable;
- 4、 Multi-function output contacts, suitable for different requirements;
- 5、 Professional access control engineering designated supporting products.

Product Parameters

Parameter	Descriptions
Input voltage	AC220V±20%
Output voltage	DC12V±15%
Output current	3A
Charge current	NO
OCP	NO
Operating ripple	≤100mV
Standard matching battery	NO
Operation temperature	-20℃ —50℃
Size	182*79*62mm
Overload protection	When the overload is overvalued or the wiring is short-circuited and the current is too large, it will automatically protect (no voltage output), and the protection tube can be used normally after cooling down (about 10 minutes) after troubleshooting.
Others	NC/NO output voltage 17V unregulated; C/NO with a maximum load of 1.5A; DC12V maximum with 1.2A load; PSUH switch signal available; CONTROL Can be connected to ±5V to ±15V electrical signal.

TEL: +86-0755-29062099-8018

For more contact methods and product information, please visit our website: www.zkradio.com

Note: The pictures and content above are for reference only. Due to the updating of products,ZKRadio will not be responsible for any disputes caused by the discrepancy between the actual and the specifications. The copyright belongs to ZKRadio Electronic Technology Co., Ltd.



Public WeChat



website